

Job Name:

Contact:

Ordering Code:

Fixture Type:

T Remote Transformer

Description

- The T series magnetic remote transformer features a metal enclosure with a covered wiring compartment for recessed mounting.
- The additional boost tap outputs on the T-300 can be used to counter voltage drop do to longer power feeds.
- Transformer must be installed in a well ventilated location to allow heat dissipation.
- IP60 rated for Indoor use only.



Technical Specs

- | | |
|---|---|
| T-60: <ul style="list-style-type: none"> - 60VA maximum - 120V AC, 60Hz input - 277V AC, 60Hz input - 12 - 15V AC outputs (boost tap) | T-300: <ul style="list-style-type: none"> - 300VA maximum - 120V AC, 60Hz input - 277V AC, 60 Hz input - 12 - 15V AC outputs (boost tap) |
| T-150: <ul style="list-style-type: none"> - 150VA maximum - 120V AC, 60Hz input - 277V AC, 60 Hz input - 12 - 15V AC outputs (boost tap) | |

Ordering Codes

Follow the steps to specify your fixture, example: T - 300 - 277V

Part Number	Wattage	Voltage
T Transformer	60 60W	120V 120V
	150 150W	277V 277V
	300 300W	

NOTES

- Under 16 feet use standard TAP.
- 16 to 25 feet use boost TAP.
- 23 to 40 feet use boost TAP with #10 wire.
- UL #505165

CAUTION

- Use either 120V or Boost TAP.
- CAP off the unused end.

