



FHSCP-UNV3-15W-L-SD-A



RoHS COMPLIANT



Emergency LED Driver

- Universal Voltage: 100-347VAC, 50/60Hz
- Output Voltage Range: 15-55V $\overline{\text{---}}$
- Output Current: 1067mA Max
- Output Wattage: 16W
- Output Type: LED Class 2
- Number of Output Channels: 1 Channel
- Dry and Damp

General Specifications

Input Voltage / Frequency	100-347VAC , 50/60Hz
Input Current	<0.1 A
Input Power	<6W
Maintain Power	<0.85W
Input Power Pass-Through Rating (AC Driver Line)	5A
Max Output Rating (LED+ LED- Terminal)	3A Max
	55V Max
Output Power	Typical 16W
Output Current Rated	1A Max
Output Voltage Range	15 - 55V $\overline{\text{---}}$
Number of Output Channels	1 Channel
Test Switch	Bi-Color(Class 2)
Input Surge Protection	3KV/6KV Ring wave, 1KV/2KV Combine surge
Protections	Output Open Protection Output Overload Protection Output Short Circuit Protection Over Temperature Protection
RFI/EMI	FCC Part15A
Ambient Operating Temperature Rang	0°C To 55°C (32°F To 131F°)
Tc	TBD
Sound Rating	A
Battery Type	Lithium-ion battery
Battery Voltage	11.1V
Pack Capacity	5000mAh
Battery Rating	55.5Wh
Battery Count	3 Cells
Battery Recharge Time	24 Hours
Battery Discharge Time	1.5 Hours Min.
IP Rating	IP20
Test Switch Remote Mounting Distance	20' (6m) Max.
Battery Connector Mounting Distance	9.84' (3m) Max.
Service Life	50,000 hours
Warranty	5 Years From the date of manufacture when properly installed
Compliance standards	UL 924, UL 1310, CSA C22.2 No.141, CSA C22.2 No.223



FHSCP-UNV3-15W-L-SD-A




RoHS COMPLIANT



Mechanical Data

Overall Dimensions	
Length	10.04" [255mm]
Width	2.05" [52mm]
Height	1.34" [34mm]





FHSCP-UNV3-15W-L-SD-A




RoHS COMPLIANT




Accessories

Test switch wire: FHS-TST-BC




Optional Accessories

Bi-Color Wet Location Test Switch: FHS-TSTWL-BC




Overall Switch Dimension



Optional Accessories

White Wet Location Test Switch: FHS-TSTWL-BC-W





FHSCP-UNV3-15W-L-SD-A




RoHS
COMPLIANT



UL
LISTED
E477042

Accessories

Wall Plate: FHSWLPWH(Pure White Wall Plate)




Wall plate and screw color:
Pure white with black lettering

Optional Accessories

Wall Plate: FHSWLPWH



Wall plate and screw color:
white with black lettering



1. "Charge push to Test" plate
2. (2) 6-32 x 1/2" LG mounting screws



FHSCP-UNV-15W-L-SD-A




RoHS COMPLIANT




UL US LISTED E477042

Wiring Diagram



Wiring Diagram (Emergency Only)





FHSCP-UNV3-15W-L-SD-A



RoHS COMPLIANT



SELF-DIAGNOSTIC INSTRUCTIONS / OPERATION:

If the self-diagnostic feature is enabled:

The emergency LED driver will conduct a self-check for sixty(60) seconds every thirty(30) days; and a ninety(90) minutes self-check every 12 months. After every self-check the LED indicator light will indicate a status signal. Check indicator status chart below to diagnose the status signal.

If the self-diagnostic feature is disabled:

User must conduct a manual test every thirty (30) days to ensure the emergency LED light source illuminates as intended. A full discharge test shall be conducted once a year; the LED light source shall illuminate for a minimum of ninety (90) minutes.

***Self-Diagnostic feature is factory enabled**

TEST SWITCH INDICATOR STATUS:

LED Indicators Status	EM Driver Status / Mode
● Solid Green	System OK / AC OK (Self-Diagnostic Enabled or Disabled)
⦿ Slow Flashing Red, 4s on / 1s off	Battery PACK not found.(Including Self-test/self-diagnostic)
⦿ Flashing Red, 1s on / 1s off	Battery PACK fault. (Including Self-test/self-diagnostic)
⦿ Flashing Green, 1s on / 1s off	Self-Diagnostic test underway
⦿ Slow Flashing Green, 0.1s on / 3s off	Normal working in EM mode. (Including Self-test/self-diagnostic)
⦿ Flashing Red, 4s on / 4s off	No load or output over voltage protection. (Including Self-test/self-diagnostic)
● Solid Red	Over current protection. (Including Self-test/self-diagnostic)
⦿ Flashing Red, 0.5s on / 3s off	Self-diagnose process current fault or Battery voltage <87.5%.
⦿ Flashing Green, 2s on / 0.5s off	Self-Diagnostic Enabled
⦿ Flashing Green, 0.5s on / 2s off	Self-Diagnostic Disabled

TEST SWITCH OPERATIONS

EM Test:

Press and hold the test button (>1s) to enter EM mode in normal AC powered.

Manual Self-Diagnostic:

After charging twelve (12) hours at least, quickly press the test button three(3) times to force the controller to enter Self-Diagnostic cycle.

Enable/Disable Self-Diagnostic Status:

Fast click 2 times within 2s to query the Self-Diagnostic Enabled/Disabled status. The indicator would blink for current status for 3 cycles. 2s ON/0.5s OFF stands for Enabled. 0.5s ON/2s OFF stands for Disabled.

Cancel reporting error:

In standby, press and hold the button for about 5s to cancel the error indication.

Turn Off EM Output:

Press and hold the test switch for 5 seconds during EM output condition to turn off EM output. This is useful for production environment to turn off the EM output once a luminaire has completed functionality testing.



FHSCP-UNV3-15W-L-SD-A



RoHS
COMPLIANT



Guidelines

Grounding

- Driver must be grounded by means of the Driver case.

Overload Protection

- If the maximum output power is exceeded, the LED driver switches off automatically, after elimination of the overload the normal operation is restored automatically.

LED Load

- Fulham's Hotspot Constant Power Emergency LED drivers are designed to drive passive LED's, COB's and LED assemblies. Proper function is not guaranteed when (LED) loads with active components are used.

Mounting and cooling

- Above an output power of 15W, the driver need to be mounted on a heat conductive surface of at least 100cm². Always test if the surface is sufficient enough before installing the LED driver.

Short Circuit Protection

- In case of a short circuit the LED driver switches to protection mode. After removal of the short-circuit the LED driver will recover automatically.

No Load Operation

- In no-load operation the output voltage will not exceed the specific open circuit output voltage.

Hot Swapping

- This driver does not support the hot swapping of the LED's.

Remote Mounting

- up to 50ft with 18AWG wire. Contact Fulham for higher remote distance.

Warranty

- Reference Fulham's limited Warranty: <https://cdn.fulham.com/PDFs/Limited-Warranty.pdf>



FHSCP-UNV3-15W-L-SD-A



Part Number Matrix

FHS

LED Driver

FHS = FireHorse HotSpot Driver

CP

Driver Type

CP = Constant Power

UNV3

Input Voltage

UNV3 = 100V-347V

15W

Max Output Power

15W = 16 Watts

L

Case Type

L = Long Case

SD

Special Features

SD = Self Diagnostic

A

Special Features

A = Conduit

Product Image: FHSCP-UNV3-15W-L-SD-A



Packaging

Master Carton



OUTER DIMENSION		
L	W	H
564mm(22.21")	414mm(16.30")	268mm(10.55")
Net Weight	Gross Weight	QUANTITY
9.3kg 20.50lb	10.5kg 23.15lb	10