## PureStyle Intelligent Color Powercore, RGBA

| Date:      |  |
|------------|--|
| Гуре:      |  |
| Firm Name: |  |
| Project:   |  |

10° x 60°, 305 mm (12 in), Narrow Beam Angle

# Premium interior concealed linear luminaire with intelligent RGBA light

Innovative PureStyle Powercore luminaires bring lighting professionals high output in a compact, easily concealed luminaire. PureStyle delivers exceptionally high-quality light for a wide range of interior applications from cove to wall-washing to backlighting and beyond. Here are just some of the powerful advantages that PureStyle brings to lighting professionals and their clients.



- Unbeatable Performance—Major innovations, including a unique optical cluster, enable PureStyle to deliver up to 800 lumens – all with superior beam quality that delivers bright, smooth light.
- Innovative Design With its compact size and an extremely short mixing distance, PureStyle can excel in areas where traditional linear luminaires are impractical. It's available in 305 mm (1 ft) and 1219 mm (4 ft) aluminium housings, as well as a range of beam angles including wide (100° x 100°), medium (30° x 60°), and narrow (10° x 60°). Interlocking connectors ensure end-to-end installation without visible light scalloping between luminaires just pure, seamless light.
- Exceptional Light All PureStyle luminaires deliver exceptional light. For applications requiring an emphasis on the orange/gold/red area of the color spectrum, we offer PureStyle iColor Powercore, RGBA.
- Superior Color Consistency Optibin, our proprietary binning optimization process, guarantees uniformity and consistency of hue across LEDs, luminaires, and manufacturing runs.

- Industry-Leading Controls PureStyle luminaires work seamlessly with the complete Color Kinetics line of controllers, including iPlayer 3, iPlayer 4, Antumbra iColor Keypad, and ColorDial Pro, or third-party controllers.
- Higher Efficiency, Lower Cost All PureStyle luminaires integrate
   Powercore technology, which controls power output to luminaires directly
   from line voltage rapidly, efficiently, and accurately. The Color Kinetics
   Data Enabler Pro merges line voltage with control, and delivers them to
   the luminaire over a single standard cable simplifying installation
   dramatically and lowering total system cost.
- Easy Installation PureStyle luminaires accept power input of 100 to 277 VAC for consistent installation anywhere in the world. Powercore allows long runs and eliminates the need for special wiring and external power supplies. For example, special connectors enable PureStyle luminaires to be connected directly (using jumper cables) with leader cables or with the terminator.

For detailed product information, please refer to the PureStyle Product Guide at www.colorkinetics.com/global/products/rgb/purestyle/



## Specifications

Due to continuous improvements and innovations, specifications may change without notice.

#### Output

| Beam Angle                           | 10° x 60° |
|--------------------------------------|-----------|
| Lumens All Channels Full On †        | 549       |
| Efficacy (lm/W) All Channels Full On | 42        |

#### **Electrical**

| Input Voltage                          | 100 to 277 VAC, auto-ranging, 50/60 Hz |
|--|--|
| Power Consumption                      | 13 W                                   |
| (Maximum at full output, steady state) |  |
| Power Factor                           | 0.9 @ 100 to 240 VAC                   |
|  | 0.85 @ 277 VAC                         |
| Surge Limits ¶                         | 1 kV maximum differential (L to N)     |

For additional Surge Protection Requirements for LED Lighting Systems, please refer to www.colorkinetics.com/KB/surge-protection.

2 kV maximum common (L to Gnd or N to Gnd)

#### Control

| Interface                                       | Data Enabler Pro (DMX or Ethernet) |
|---|------------------------------------|
| Control Channels                                | 4 channels per 1 ft section        |
| For additional Control Channel information, ple | ease refer to https://             |
| colorkinetics helpdocs io/article/fv5rkpvclg    |                                    |

#### **Control System**

Color Kinetics full range of controllers, including iPlayer 3, iPlayer 4, Antumbra iColor Keypad, and ColorDial Pro, or third-party controllers

Remote Monitoring & Management Works with Interact Landmark

#### **Lumen Maintenance**

#### Ambient

| Threshold§ | Temperature    | Reported ¶¶          | Calculated ¶¶       |
|------------|----------------|----------------------|---------------------|
| L 90       | 25 °C          | 11,300               | 11,300              |
|            | 50 °C          | 11,300               | 11,300              |
| L 80       | 25 °C          | 35,700               | 35,700              |
|            | 50 °C          |                      | 35,700              |
| L 70       | 25 °C          | > 54,000             | 63,300              |
|            | 50 °C          | > 54,000             | 63,300              |
| L 50       | 25 °C          | > 54,000             | > 100,000           |
|            | 50 °C          | > 54,000             | > 100,000           |
|            | 50 °C<br>25 °C | > 54,000<br>> 54,000 | 63,300<br>> 100,000 |

#### **Physical**

Humidity

| Dimensions                | 58.5 x 298.8 x 40 mm (2.3 x 11.75 x 1.57 in)            |
|---------------------------|---|
| (Height x Width x Depth)  |   |
| Weight                    | 0.5 kg (1.1 lb)   |
| Housing Material          | Extruded anodized aluminium, white powder-coated finish |
| Lens                      | Polycarbonate   |
| Luminaire Connections     | Integral male/female connectors                         |
| Temperature Range         | s   |
| -20 to 50 °C (-4 to 122 ° | F) Operating  |
| -20 to 50 °C (-4 to 122 ° | F) Startup  |
| -40 to 80 °C (-40 to 176  | °F) Storage   |

0 to 95%, non-condensing

#### Thermal Protection enabled

For additional Thermal Protection information, please refer to https://colorkinetics.helpdocs.io/article/sh301ducix

#### **Luminaire Run Lengths**

To calculate luminaire run lengths and total power consumption for your specific installation, download the Configuration Calculator from www.colorkinetics.com/support/install\_tool/

#### **Certification and Safety**

| Approbation                                  | UL/cUL, FCC Class B, CE, PSE, CQC, RCM |
|--|--|
| Environment                                  | Dry/Damp Location, IP20                |
| For additional Energy Efficiency Class Infor | mation, please refer to https://       |
| colorkinetics helpdocs io/article/cyiis2p8gg | ר                                      |






<sup>†</sup> Lumen measurement complies with IES LM-79-08 testing procedures.

<sup>§</sup> Lxx = 50% lumen maintenance (when light output drops below 50% of initial output). All values are given at B10, or the median value where 90% of the LED population is better than the reported or calculated lumen maintenance measurement.

 $<sup>\</sup>P$  Minimum surge limits per IEC 61547, tested in accordance with IEC 61000-4-5.

<sup>¶¶</sup> Lumen maintenance figures are based on lifetime prediction graphs supplied by LED source manufacturers. Whenever possible, figures use measurements that comply with IES LM-80-08 testing procedures. In accordance with TM-21-11, Reported values represent the interpolated value based on six times the LM-80-08 total test duration (in hours). Calculated values represent time durations that exceed six times the total test duration.

### **Dimensions**




## Photometrics 10° x 60°, 305 mm (12 in)

Photometric data is based on test results from an independent NIST traceable testing lab. IES data is available at www.colorkinetics.com/global/support/ies.


| Beam Angle                           | 10° x 60°            |
|--------------------------------------|----------------------|
| LED                                  | All channels full on |
| Lumens All Channels Full On          | 549.0                |
| Efficacy (lm/W) All Channels Full On | 42                   |



#### Polar Candela Distribution



#### Illuminance at Distance



#### **Zonal Lumen**

| Zone   | Lumens | % | Luminaire |
|--------|--------|---|-----------|
| 0-30   | 425.8  |   | 73.7%     |
| 0-40   | 519.1  |   | 89.8%     |
| 0-60   | 566.3  |   | 98.0%     |
| 0-90   | 577.8  |   | 100.0%    |
| 60-90  | 11.5   |   | 2.0%      |
| 70-100 | 3.8    |   | 0.7%      |
| 90-120 | 0.0    |   | 0.0%      |
| 90-180 | 0.0    |   | 0.0%      |
| 0-180  | 577.9  |   | 100.0%    |
|        |        |   |           |

For lux multiply fc by 10.7

#### Coefficients of Utilization - Zonal Cavity Method

|       |      |      |      |      |      |      |      |      | Effe | ecti | ve   | Floor | Ca   | vity | Refle | ctar | nce: | 20%  |
|-------|------|------|------|------|------|------|------|------|------|------|------|-------|------|------|-------|------|------|------|
| RCC % | :    | 8    | 30   |      |      | - 1  | 70   |      |      | 50   |      |       | 30   |      |       | 10   |      | 0    |
| RW %  | :70  | 50   | 30   | 0    | 70   | 50   | 30   | 0    | 50   | 30   | 20   | 50    | 30   | 20   | 50    | 30   | 20   | 0    |
| RCR   | :    |      |      |      |      |      |      |      |      |      |      |       |      |      |       |      |      |      |
| 0     | 1.19 | 1.19 | 1.19 | 1.19 | 1.16 | 1.16 | 1.16 | 1.00 | 1.11 | 1.11 | 1.11 | 1.06  | 1.06 | 1.06 | 1.02  | 1.02 | 1.02 | 1.00 |
| 1     | 1.14 | 1.11 | 1.09 | 1.06 | 1.11 | 1.09 | 1.07 | 0.94 | 1.05 | 1.03 | 1.01 | 1.01  | 1.00 | 0.98 | 0.98  | 0.97 | 0.96 | 0.94 |
| 2     | 1.08 | 1.04 | 1.00 | 0.96 | 1.06 | 1.02 | 0.98 | 0.88 | 0.99 | 0.96 | 0.93 | 0.96  | 0.93 | 0.91 | 0.93  | 0.91 | 0.89 | 0.88 |
| 3     | 1.03 | 0.97 | 0.92 | 0.88 | 1.01 | 0.96 | 0.91 | 0.83 | 0.93 | 0.89 | 0.86 | 0.91  | 0.88 | 0.85 | 0.88  | 0.86 | 0.84 | 0.82 |
| 4     | 0.98 | 0.91 | 0.86 | 0.82 | 0.97 | 0.90 | 0.85 | 0.78 | 0.88 | 0.84 | 0.81 | 0.86  | 0.82 | 0.80 | 0.84  | 0.81 | 0.79 | 0.77 |
| 5     | 0.94 | 0.86 | 0.81 | 0.76 | 0.92 | 0.85 | 0.80 | 0.74 | 0.83 | 0.79 | 0.75 | 0.82  | 0.78 | 0.75 | 0.80  | 0.77 | 0.74 | 0.73 |
| 6     | 0.90 | 0.81 | 0.76 | 0.72 | 0.88 | 0.81 | 0.75 | 0.70 | 0.79 | 0.75 | 0.71 | 0.78  | 0.74 | 0.71 | 0.77  | 0.73 | 0.70 | 0.69 |
| 7     | 0.86 | 0.77 | 0.72 | 0.68 | 0.85 | 0.77 | 0.71 | 0.66 | 0.75 | 0.71 | 0.67 | 0.74  | 0.70 | 0.67 | 0.73  | 0.69 | 0.66 | 0.65 |
| 8     | 0.82 | 0.74 | 0.68 | 0.64 | 0.81 | 0.73 | 0.68 | 0.63 | 0.72 | 0.67 | 0.64 | 0.71  | 0.67 | 0.63 | 0.70  | 0.66 | 0.63 | 0.62 |
| 9     | 0.79 | 0.70 | 0.65 | 0.61 | 0.78 | 0.70 | 0.64 | 0.60 | 0.69 | 0.64 | 0.61 | 0.68  | 0.64 | 0.60 | 0.67  | 0.63 | 0.60 | 0.59 |
| 10    | 0.76 | 0.67 | 0.62 | 0.58 | 0.75 | 0.67 | 0.61 | 0.57 | 0.66 | 0.61 | 0.58 | 0.65  | 0.61 | 0.58 | 0.64  | 0.60 | 0.58 | 0.56 |

## Luminaire and Accessories

Use Item Number when ordering in North America

| Luminaire   | Item Number   | Item 12NC    |
|---|---------------|--------------|
| PureStyle Intelligent Color Powercore, RGBA, 10° x 60°, 305 mm (12 in), Narrow Beam Angle | 123-000026-02 | 912400133456 |
| Accessories   |               |              |
| Leader Cable, UL, 3 m (10 ft)   | 108-000065-00 | 912400133637 |
| Leader Cable, CE/CCC, 3 m (10 ft)   | 108-000065-01 | 912400133638 |
| Jumper Cable, UL, 305 mm (1 ft)   | 108-000066-00 | 912400133639 |
| Jumper Cable, CE/CCC, 305 mm (1 ft)   | 108-000066-01 | 912400133640 |
| Mounting Track, White   | 120-000194-00 | 912400133643 |
| Wiring Compartment, UL  | 120-000191-00 | 912400133644 |
| Louver, 305 mm (1 ft)   | 120-000192-02 | 912400133647 |
| End Of Run Diffusers, Bag of 10   | 120-000196-00 | 912400134527 |
| PureStyle & PureStyle Compact Masking Plate, 305 mm (1 ft)                                | 120-000213-01 | 912400136912 |
| Power Supplies  |               |              |
| Data Enabler Pro, 3/4 in / 1/2 in NPT (U.S. trade size conduit)                           | 106-00004-00  | 910503701210 |
| Data Enabler Pro, PG21/PG13 (metric size conduit)   | 106-00004-01  | 910503701211 |

