

## LED CYLINDERS INSTALLATION INSTRUCTIONS


**CYL SERIES** 

## IMPORTANT:

Read all instructions before installing luminaire. Retain for future reference.

SAFETY: This luminaire must be wired in accordance with local electrical codes and ordinances.

Carefully observe grounding procedure under "electrical connection" section. This product must be installed by a licensed electrician. Conform to your local building codes. WARNING: Make certain power is OFF from the electrical panel before starting installation or attempting any maintenance.



The parts included in the packaging:

- Cylinder housing
- Reflector
- Inner reflector
- Ballast / driver tray
- Cover (Canopy)




1. The wires are tied up for shipping purpose. Untie them.



Do the supply wire connections in the J-box (by others) as per the local electrical code. A certified electrician must do the connections. Install the cover (canopy) over the J-box.




3. Do the connections to the ballast/driver tray, as per the local



Install the Ballast/Driver tray on the cover (canopy) and 4. secure it three screws.



5. Do the connection to the light engines. A certified electrician must do the connections.



Install the housing over the ballast driver tray and secure it with the 4 screws.



7. Install the reflector and secure it with two screws.



8. Finally install the inner reflector.

